



F21 Transmisor (solo) 4 botones Velocidad Doble

Características Esenciales

- 1 Años de Garantía, Servicio y Atención al Cliente en Mexico

Especificaciones Técnicas

Channels	4	Control Speed	1 Speed
Transmitter Emergency Stop	Yes	Codigo FCC	2AZMK-Q1212
Fuente de Alimentación del Transmisor	2 AA batteries	Distancia de Control	300 ft up to 600 ft with optional antenna
Código de Seguridad	32 bits (4.3 billion)	Potencia del Transmisor	≤10dBm
Rango de Frecuencia	VHF: 310~331 MHz; UHF: 425 ~ 446 MHz	Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C
Normas	FCC and OSHA standard 1910.179	Garantía	1 Year

F21-4S/4D TRANSMITTER
Economical, safe, convenient



MODEL: F21-4S-TX
ITEM CODE: 921-004-001
Dimensions: 156 x 61 x 51 mm
Weight: 255g (without batteries)

Product Features:

- 4 buttons (D means double steps), spare button
- 8 control contactors.
- With battery voltage warning device, the power supply is cut off during low power.
- Program the button function by computer interface.
- Up/Down, East/West can be programmed to interlock or non-interlock.
- The spare button can be programmed to start, toggle or normal, etc.

Standard Configuration:

- One transmitter (with hanging belt)
- One dust bag
- One receiver
- Receiver with 1.6 meter cable
- Battery: One pair
- One receiver antenna.
- Operation and maintenance manual.

Safety features:

Each radio remote control system functions in all manner of operational conditions equipped with their own unique identity code (ID-Code). This means that only the correct control unit can activate and control its matching receiver (crane/machine) for maximum safety. The system is FCC and CE certifies.



Peso & Dimensiones

Peso Total 1 lbs / 1 Kg

Detalles del Empaque

Paquete 1 Peso Neto 1 lbs / 1 Kg

Paquete 1 Peso Bruto 1 lbs / 1 Kg

Paquete 1 Profundidad 9 in / 23 cm

Paquete 1 Ancho 4 in / 11 cm

Paquete 1 Altura 4 in / 11 cm

Referential Images / Imágenes Referenciales
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso