



Control Remoto largo alcance 300 m - 12 Botones Una Velocidad - Multivoltage

Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 3 Años de Garantía, Servicio y Atención al Cliente en Mexico

Especificaciones Técnicas

Codigo FCC	2AZMK-Q1212	Botones	12
Fuente de Alimentación del Transmisor	2 AA batteries	Material	PA6 30% GF
Fuente de Alimentación del Receptor	AC/DC110V-480V	Sensibilidad del Receptor	dBm -112
Distancia de Control	900 ft / 300 mt	Código de Seguridad	200 Millions
Potencia del Transmisor	≤10dBm	Rango de Frecuencia	433/480 MHz
Protección IEC Motor	IP65	Parada de Emergencia	YES
Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C	Garantía	3 Year

Peso & Dimensiones

A Altura Total	8
D Depth	0.6"
W Ancho	2.1"
Peso Total	6 lbs / 3 Kg

Detalles del Empaque

Paquete 1 Peso Neto	6 lbs / 3 Kg
Paquete 1 Peso Bruto	6 lbs / 3 Kg
Paquete 1 Profundidad	12 in / 31 cm
Paquete 1 Ancho	8 in / 21 cm
Paquete 1 Altura	5 in / 13 cm

Referential Images / Imágenes Referenciales
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso