



## Radio Remote Control 2 Channels 2 Speed Multi voltage Range 300 ft

## **Características Esenciales**

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Servicio y Atención al Cliente en Mexico

## **Especificaciones Técnicas**

Transmitter Emergency Stop	Yes	Control Speed	2 Speed
Channels	2	Codigo FCC	2AZMK-Q1212
Botones	3	Fuente de Alimentación del Transmisor	2 AA batteries
Fuente de Alimentación del Receptor	AC 110V-480V	Sensibilidad del Receptor	dBm -112
Distancia de Control	300 ft / 100 mt	Código de Seguridad	200 Millions
Potencia del Transmisor	≤10dBm	Rango de Frecuencia	433/480 MHz
Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C	Normas	FCC and OSHA standard 1910.179
Garantía	1 Year	Wireless Control IP Protection	IP65



## Peso & Dimensiones Detalles del Empaque

Peso Total	4 lbs / 2 Kg	A Altura Total	5.3"
		D Depth	1.2"
		W Ancho	2.7"

Referential Images / Imágenes Referenciales Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso