



Radio Remote Control 2 Channels 2 Speed Multi voltage Range 300 ft

Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Servicio y Atención al Cliente en Mexico

Especificaciones Técnicas

Channels	2	Control Speed	2 Speed
Transmitter Emergency Stop	Yes	Código FCC	2AZMK-Q1212
Botones	3	Fuente de Alimentación del Transmisor	2 AA batteries
Fuente de Alimentación del Receptor	AC 110V-480V	Sensibilidad del Receptor	dBm -112
Distancia de Control	300 ft / 100 mt	Código de Seguridad	200 Millions
Potencia del Transmisor	≤10dBm	Rango de Frecuencia	433/480 MHz
Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C	Normas	FCC and OSHA standard 1910.179
Garantía	1 Year		

Peso & Dimensiones

A Altura Total	5.3"
D Depth	1.2"
W Ancho	2.7"
Peso Total	4 lbs / 2 Kg

Detalles del Empaque

Paquete 1 Peso Neto	5 lbs / 3 Kg
Paquete 1 Peso Bruto	4 lbs / 2 Kg
Paquete 1 Profundidad	12 in / 31 cm
Paquete 1 Ancho	10 in / 26 cm
Paquete 1 Altura	4 in / 11 cm

Referential Images / Imágenes Referenciales
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso