



Control Remoto largo alcance 300 m - 6 Botones Doble Velocidad - Multivoltage

Características Esenciales

- 200 Auto Channels replacing traditional single channel quartz plus 1 Million ID Codes.
- Easy Pairing System, no need of software or copier to add or replace lost or broken Transmitter
- Customizable 200 Functions settings to meet any special requirements
- Reinforced fiber plastic case for Transmitter and Receiver plus rubber protector for Transmitter
- 1 Años de Garantía, Servicio y Atención al Cliente en Mexico

Especificaciones Técnicas

Channels	6	Control Speed	2 Speed
Transmitter Emergency Stop	Yes	Codigo FCC	2AZMK-Q1212
Capacidad Contactor	10A	Botones	7
Fuente de Alimentación del Transmisor	2 AA batteries	Fuente de Alimentación del Receptor	AC 110V-480V
Sensibilidad del Receptor	dBm -112	Distancia de Control	900 ft / 300 mt
Código de Seguridad	200 Millions	Potencia del Transmisor	≤10dBm
Rango de Frecuencia	433/480 MHz	Rango de temperatura de Trabajo	-40 ~ 185 °F / -40 ~ 85°C
Normas	FCC and OSHA standard 1910.179	Garantía	1 Year

Peso & Dimensiones

A Altura Total	6.68"
D Depth	0.6"
W Ancho	2.1"
Peso Total	6 lbs / 3 Kg

Detalles del Empaque

Paquete 1 Peso Neto	6 lbs / 3 Kg
Paquete 1 Peso Bruto	6 lbs / 3 Kg
Paquete 1 Profundidad	12 in / 31 cm
Paquete 1 Ancho	8 in / 21 cm
Paquete 1 Altura	5 in / 13 cm

Referential Images / Imágenes Referenciales
Specifications may change without notice / las especificaciones pueden cambiar sin previo aviso